

Product: Tachometer	Description <b>ERRATIC OPERATION</b>	Date Aug 03
Type: Electrical		Issue 1

**To Reduce or Eliminate Erratic Operation in Tachometers**

1. Purchase diode #1N4005 from your local electronics store.
2. Cut both ends of the diode so each is approx. 3/ 4" long.
3. Crimp a 1/ 4" female spade connector on the end of the diode with the silver band.
4. Crimp a butt-splice connector on the other end of the diode.
5. Crimp the opposite end of the butt-splice connector to the wire connected to ignition signal source.
6. Connect 1/ 4" female spade connector used in step # 3 above to terminal # 4 on the back of the tachometer.
7. Connect a ground (-) wire to terminal # 3.
8. Connect a switched 12-volt power wire to terminal # 2.
9. Set switches for the appropriate number of cylinders.